

PAZ-5006,6 zone amplifier CKS



The PA mixer amplifier is designed for small/medium commercial audio solutions with 6 zones, each zone can be set to a different output volume.

The 19" rack mixer amplifier with built-in audio source player integrates zone paging controller, preamplifier, power amplifier and media player into a single 2U high device, its power rating is 500W, it has 3 microphone inputs and 2 auxiliary inputs.

It supports 100V/70V and 4-16 ohm speaker applications. Features: 6 zone amplifier for public address (PA). 19" amplifier for mounting in a 2U high rack.

Power rating 500W 6 zone 100V speaker output. 4-16Ohm-70V-100V speaker zone outputs. 6 zone speaker outputs with independent volume control. Built-in MP3 player has USB and SD, FM tuner, bluetooth.

With an IR remote to switch source and control volume. 3 mic inputs, Mic1 (6.3mm) and Mic/Line input 2-3-4 (XLR) . Balanced Mic2-3-4 input with mic/line switch and 48V phantom power. Mic1 VOX function with highest input priority, except EMC input. Overload, short circuit and high temperature protection.

M szaki adatok PDF	
Description	PA 6 Zone Mixer Amplifier with Mp3 & Tuner
Power rating (RMS)	500W
Audio output	100V / 70V / 4-16 ohm
Audio inputs	Mic1-4: 2.5mV, Line1-2: 250mV; EMC: 250mV
Media player	MP3 via USB and SD, FM tuner, Bluetooth
Zones	6
Frequency	80 - 16.000 Hz
THD	<0.1%
S/N ratio	>70dB
Power supply	AC230V, 50-60Hz ; DC24V
Power consumption, operation	650W
Dimensions	484x405x88mm
Weight	10.4 Kg

