

Loudspeaker with Mylar cone for use in entry phones, alarms, intercoms, transistors, headphones...
Especially for outdoors.



FE-3850M

LOUDSPEAKER	3" = 76 mm
POWER	5 W
IMPEDANCE	8 Ohm
SENSITIVITY	91 dB at 1 W/1 m
SOUND PRESSURE	97 dB at 1 m
MAGNET	Ferrite
CONE	Mylar
WEIGHT	0.2 kg
DIMENSIONS	Total: 77 x 77 x 32 mm depth Insert: 77 mm Ø x 30 mm depth