

Loudspeaker with Mylar cone for use in entry phones, alarms, intercoms, transistors, headphones...  
Especially for outdoors.



### **FE-4815M**

LOUDSPEAKER	4" = 102 mm
POWER	15 W
IMPEDANCE	8 Ohm
SENSITIVITY	91 dB at 1 W/1 m
SOUND PRESSURE	100 dB at 1 m
MAGNET	Ferrite
CONE	Mylar
DIMENSIONS	Total: 102 x 102 x 41 mm depth Insert: 101 mm Ø x 38 mm depth
WEIGHT	0.4 kg