

**PA-1200IRD, Internet radio, DAB+/FM RDS tuner insertion with USB port**



Internet radio, DAB+/FM RDS tuner insertion with USB port, for PA mixing amplifier with insertion compartment.

- LAN or WLAN connection, WPS possible
- Detachable WLAN antenna
- Network Setup Wizard
- FM tuner with RDS
- 30 presets for your favourite radio stations (Internet radio 10x, DAB+ 10x, FM 10x)
- App control with the UNDOK™ app
- USB storage media can be connected directly
- Media streaming of shared files shared on the network (UPnP server)
- Reproduction of MP3 and WAV files
- Display of file name
- Easy folder navigation
- Alphanumeric LCD
- Automatic switch-on after power failure (autostart)
- Storage of settings and operating modes
- Snooze function can be set
- Alarm function

M szaki adatok PDF	
Description	Internet radio, FM RDS and DAB+ tuner, USB player
Media	streaming, FM, DAB+, MP3, WAV, LAN/WLAN, USB
Power supply	DC 17 V/500 mA
Mains voltage	DC 17 V
Admiss. ambient temp.	0-40 °C
Dimensions	195 x 40 x 135 mm
Weight	360 g
Connections	1 x RJ45 (LAN) 1 x IEC/coaxial plug for FM/DAB+ antenna 1 x SMA jack for WLAN antenna
Packing dimensions (W x H x L)	0.22 x 0.17 x 0.06 m
Gross weight	0.565 kg