

SX1845/4

18" Lf Driver



MOUNTING INFORMATION

| | |
|------------------------|---------|
| Overall Diameter | 460 mm |
| Bolt Circle Diameter | 440 mm |
| Baffle cutout Diameter | 424 mm |
| Depth | 220 mm |
| Net Weight | 16.7 Kg |

SPECIFICATIONS

| | |
|---------------------|------------|
| Nominal Impedance | 4 Ohm |
| RMS Power | 1500 W |
| MAX Power | 3000 W |
| Sensitivity (1W/1m) | 98 dB |
| Frequency Range | 38-1200 Hz |
| Voice Coil Diameter | 114 mm |
| Magnet weight | 167 Oz |
| Basket Material | Ferrite |

THIELE AND SMALL PARAMETERS

| | |
|------------|----------------------|
| Fs | 38 Hz |
| Re | 5.0 Ohm |
| Qes | 0.32 |
| Qms | 13 |
| Qts | 0.31 |
| Vas | 128 L |
| Sd | 1220 cm ² |
| Xmax | 12.5 mm |
| Mms | 286 gr |
| Bl | 32 T/m |
| Efficiency | 2.1% |
| EBP | 118 |