

MA13W/8

MA13W/8



MOUNTING INFORMATION

Overall Diameter	130 mm (5")
Bolt Circle Diameter	138 mm
Baffle cutout Diameter	114 mm
Depth	58 mm
Mounting Depth	51 mm
Net Weight	0.6 Kg

SPECIFICATIONS

Nominal Impedance	8 Ohm
Output power	80 W
Sensitivity (1W/1m)	91 dB
Frequency Range	80-6000 Hz
Voice Coil Diameter	25 mm
Magnet	Ferrite
Magnet weight	10 Oz
Basket Material	Steel

THIELE AND SMALL PARAMETERS

Fo	95.349 Hz
Re	4000 Ohm
Qes	1,358
Qms	3,053
Qts	0,94
Vas	3,685 l
Sd	75,43 m ²
Mms	7.057 g
Bl	3.955 Tm
Kxm	11.203 mmH
Mmd	6.680 mkg
Cms	456.054 uM/N
Efficiency	0.20%